



Antenna Splitter

T-59FP



Description

A pair of antennas can be divided into 4 receivers (one for two) to expand the wireless microphone system. At the same time, it has 2 cascade signal outputs for expanding the antenna distribution system.

Feature

- *It has 2 antenna input interfaces, supports receiving antenna signals, and achieves the effect of distributing multiple RF signals.
- *It has 10 antenna signal output interfaces, which can distribute a pair of antennas to 5 (one-to-two) receivers.
- *It has two antenna cascade interfaces, supports unlimited cascade distributors, and can achieve the purpose of expanding wireless microphones.
- *It has 4 DC power output interfaces, supports powering 4 receivers, reduces the number of adapters and eliminates cumbersome wiring.

Specification

Frequency Range	470-950MHZ
Total gain	10dB
Input/output impedance	50Ω
Antenna power supply	9V
Signal input interface	BNC interface×2
Signal output interface	BNC interface×8
Signal cascade interface	BNC interface×2
DC output interface	12V DC/3A (MAX) × 4 groups, the center point is the positive pole
Power supply	12V DC/3A
Connector port	BNC
Dimensions (L×W×H)	482.6×209.2×45mm
Weight	2.25kg