



Description

The wireless two-button lighting panel is a switch powered by a single live wire, which can realize dual-channel power control. It can directly replace ordinary switches without rewiring. It is widely used in intelligent control to link with central control to control intelligent equipment, such as lights, curtains, etc.

Feature

- * Using wireless digital identification technology, each switch has its own independent control code and will not interfere with each other.
- * Support manual and remote control functions, non-directional, and can pass through walls.
- * Adopt standard electrical symbol identification, 86 bottom box installation, live wire control installation, and the wiring is exactly the same as that of ordinary mechanical wall switches.
- * Applicable to various types of standard lamps, no need to connect additional peripheral devices.
- * The switch and the wireless gateway adopt intelligent sub-key recording code, which can feedback the switch status in real time.
- * Using frequency modulation technology, strong anti-interference ability, long receiving distance, multiple switches installed together will not interfere with each other.



Specification

Working frequency	400-451MHz
Shell material	Flame retardant ABS+PC
Transmit power	10dBm
Receive sensitivity	-110dBm
Load rated power (resistive load)	5~600W per channel, maximum 1200W (when using fluorescent lamps, energy-saving lamps, and LED lamps, the connected load cannot exceed one-third of the resistive load)
Standby power consumption	< 0.007W
Power supply	Single live wire power supply, AC220V±10% 50/60HZ
Dimensions (L*W*H)	86mm*88mm*39mm
Operating temperature	-10°C~45°C
Working humidity	<90%, no condensation
Net weight	0.129kg