



## Description

FM/AM board is used to receive FM and AM broadcast signals and directly access to PA system.

## Feature

- \* FM and AM broadcast reception.
- \* Support channel search operation on the remote control station interface.
- \* Report the working status of the equipment: online status, failure status, etc.
- \* Support the use of any board position in the broadcast cabinet.

## Specification

Supporting board quantity	Maximum of 4
Network interface	RJ45*1, 10/100Mbps adaptive, IGMP and TCP/IP protocol
FM antenna	Single wire antenna 1.5m
AM antenna	Loop antenna
FM broadcast	Frequency range 64-108MHz, sensitivity $\leq 20\mu\text{V}$
AM broadcast	Frequency range 520-1710kHz, sensitivity $\leq 300\mu\text{V}$
IF frequency	45KHz/128KHz
Size	312.6mm×129mm×30mm
Weight	0.25kg