



## Active Speaker

### T-2100BH



## Description

Used in multimedia classrooms, lecture halls , training rooms and other places where sound amplification is required.

## Feature

- \*Supports 1-channel microphone , 1-channel stereo line input and line output .
- \*It has output overload, overvoltage and short circuit protection functions .
- \*With mute function, 100V broadcast input takes precedence over line input.
- \*It has 1 microphone volume adjustment, 1 line input volume adjustment, and 2 treble and bass adjustments.
- \*Built-in HIFI high-fidelity high-end speakers, built-in electronic crossover, high and low frequency units with independent power amplifier drive for better sound quality.
- \*With 100V broadcast priority input interface.

## Specification

Rated output power	2×100W
Output impedance	4Ω
Input sensitivity	AUXIN:350mV±20mV/10KΩ;MIC:5mV±0.5mV
Tone adjustment	LF:(0dB ~-6dB)@100Hz;HF:(0dB ~-6dB)@10KHz
Signal-to-noise ratio (A-weighted)	MIC≥73dB;AUX≥85dB
Frequency response	40~20KHz(±3dB)
Harmonic distortion	≤1%
Line Output	1V
Volume adjustment	MIC volume, AUX volume, treble, bass
Input voltage	~220V 50Hz
Power consumption	55W
Product size	280.3×275×400
Product weight	17.5kg

\*Measured according to GB4943.1 test method (at 1/8 power)