



# Console

## TL-SL712



### Feature:

- \* 4096 DMX channels, provide 6 photoelectric isolation DMX output ports and network extension ports; support multiple standard DMX network protocols, and transmit DMX512 signals through the network.
- \* 10.4" TFT-LCD touch screen, Chinese and English operation interface; support window switching function on the touch screen.
- \* Provide a VGA monitor interface to display the edited program information.
- \* 24 playback program fader × 30 pages and 20 fixed program buttons × 20 pages, a total of 1120 playback programs can be saved. Support a maximum simultaneous output of 24 faders + 20 buttons, a total of 44 playback programs.
- \* 4 photoelectric data control wheels.
- \* A maximum of 400 lamps can be controlled.
- \* A maximum of 400 lamp groups can be stored.
- \* A maximum of 400 material data can be edited.
- \* A maximum of 400 user graphics can be stored.
- \* A maximum of 400 records of macro performances can be stored.
- \* Multi-option keypad. Multiple options such as groups, lamps, materials, user graphics, and macro performances are provided. It is convenient for users to do multi-page selections with the touch screen.
- \* Independent color mixing system control wheel. It is especially convenient to control LED lights and computer lights with CMY or RGB channels.
- \* Built-in various graphics running effects, provide a variety of parameter settings to create endless changes, and support being saved as user graphics.
- \* Provide the program priority function; the performance program can be individually set to 5 levels: lowest, low, normal, high, and highest. The higher one will run first.
- \* The performance program can be paused separately in real time.
- \* Flash jog trigger function.
- \* Built-in nearly 8000 kinds of computer light library data, compatible with R20 lamp library. The user can edit the system lamp library or create a new user lamp library.
- \* Support the standard MIDI device control, support multiple consoles working together in a master-slave manner, and support external MIDI time code trigger and internal clock for light show with one key.
- \* A/B field switching function, support A or B zone playback output.
- \* The website supports free download of upgrade files such as lamp library and system version.
- \* Built-in electronic hard disk supports performance program backup and running data storage.
- \* With a USB interface, you can use a U disk to store multiple user performance files and system backup files.
- \* Dimmable 12V gooseneck work light.

### Specifications:

Model	TL-SL712
Input voltage	AC 110-240V 50/60Hz
Fixture size (L×W×H)	650×490×130mm
Package size (L×W×H)	720×660×260mm
Gross weight	30kg
Net weight	14.2kg