



Terminal Detector

VA-6000T



Description:

- * Integrated aluminum body, elegant appearance.
- * To be installed at the end of each speaker loop, work with VA-6000MS/VA-P8500S to detect the status of the speaker loop.
- * No need external power supply, easy installation and wiring.
- * No need external power supply, convenient for engineering wiring and installation.

Specifications:

Model	VA-6000T
MAX Current	0.01A
Power consumption	≤1W
Machine Index	
Size (L x W x D)	156 x 32 x 48mm
Weight	About 200g
Installation	Desktop or Wall mounted
Color	Black
Environment Requirements	
Operation Temp	+5°C ~ +40°C
Storage Temp	-20°C ~ +70°C
Relative Temp	<95% (No condensation)