



Description

The DC power board, used in the broadcast controller cabinet and power amplifier cabinet, provides power for the cabinets and the boards when the AC power supply is cut off.

Feature

- * Supply power for the cabinet board;
- * Support the indication of the working status of the board;
- * Support the power supply switching with the AC power board.
- * Support the use of any board position in the cabinet;
- * Support 2 power boards in 1 cabinet at the same time for redundant power supply.

Specification

Input voltage	DC19-31V, rated 24V
Maximum input current	50A
Output voltage	±85V, +24V
Maximum output current	11A, 3A
Heat dissipation mode	Forced air cooling
Protection mode	Overvoltage and undervoltage protection, overcurrent protection, high temperature protection
Dimension	312.6mm×129mm×60mm
Weight	1.6kg