




Digital AM/FM Tuner

T-6228



Remote control

Feature:

- * 1U tabletop and rack mount with aluminum alloy panel.
- * Clear LCD display, microcomputer control and touch-button operation.
- * FM/AM two-band receiving option, FM receiving frequency: 76MHz ~ 108MHz, AM receiving frequency: 520KHz ~ 1708KHz.
- * Radio frequency automatic search and memory function, maximum radio memory of 99bands, and a power-off memory function.
- * It adopts vehicle-dedicated digital radio module, integrated radio tuner module, featuring a small size, good performance and strong anti-interference, etc.
- * Support infrared remote control.
- * 1-channel audio signals left and right channels (L / R) output.
- * There is an address dial switch to set the address of the machine and meet the address confirmation when multiple devices are used together.
- * Built-in high-fidelity wideband monitor speaker, full and clear sound; a monitor with adjustable volume knob.

Specifications:

Model	T-6228
Power Supply	~220V 50Hz
Power Consumption	30W
Dimension	484×290×44mm
Weight	3.24Kg