



Description :

The smart switch is a self-generating switch that requires no wiring and no batteries. It has a built-in Mesh wireless communication module, which can perform wireless data transmission. It can work with interactive smart sensors, edge gateways and other devices in the smart building system, and supports lighting control and linkage.

Feature :

- * No wiring required, easy to install.
- * Press to generate electricity without batteries, environment friendly.
- * Reliable quality, the button can withstand 100,000 repeated presses.

Specification:

Model	TI-LS1
Control button	1
Output power	+0dBm
Transmission distance	15 meters
Communication protocol	BLE
BLE channel	37/38/39(2402MHz/2426MHz/2480MHz)
Button strength	About 500g
Button stroke	About 4mm key end stroke
Service lifespan	> 100,000 times
Housing material	PC material
Weight	0.1kg
Dimension	86*86*15mm